ELECTRICAL SYMBOL LEGEND

SOME SYMBOLS AND ABBREVIATIONS MAY NOT BE USED FOR THIS PROJECT.

A. GENERAL

- JUNCTION BOX (4" SQUARE MINIMUM)
- INDICATES HOMERUN.
- CIRCUIT CONDUCTORS. LONG DASH INDICATES NEUTRAL CONDUCTOR, SHORT DASH INDICATES PHASE CONDUCTORS. CODE SIZED EQUIPMENT GROUND NOT INDICATED BUT REQUIRED.
- ISOLATED GROUNDING CONDUCTOR. GREEN, INSULATED WITH YELLOW STRIPE.
- GROUNDING CONDUCTOR. GREEN, INSULATED, SIZE PER PLAN.
- SURFACE PANELBOARD
- FLUSH PANELBOARD
- TRANSFORMER. (KVA SIZE AS NOTED). GROUNDING SYSTEM TO BUILDING STEEL. (IF APPLICABLE).
- CONDUIT STUB-UP ABOVE CEILING
- CONDUIT STUB-DOWN TO FLOOR BELOW
- CONDUIT IN UNDERGROUND/SLAB
- CONDUIT STUB-UP WITH CAP
- CONDUIT SEAL-OFF
- FLEXIBLE CONDUIT. PROVIDE LIQUID TIGHT FLEX IN WET OR EXTERIOR LOCATIONS AND AT CONNECTIONS TO VIBRATING EQUIPMENT AND/OR TRANSFORMERS.
- CONDUIT CONCEALED IN WALLS OR ABOVE CEILING.

B. POWER

- 20A SPEC GRADE SINGLE RECEPTACLE MOUNTED AT +15" TO BOTTOM OR AS NOTED
- 20A SPEC GRADE DUPLEX RECEPTACLE MOUNTED AT +15" TO BOTTOM OR AS NOTED
- 20A SPEC GRADE FOURPLEX RECEPTACLE MOUNTED AT +15" TO BOTTOM OR AS NOTED
- 20A SPEC GRADE DUPLEX CONVENIENCE OUTLET MOUNTED ABOVE COUNTER. VERIFY EXACT HEIGHT WITH ARCHITECTURAL ELEVATIONS.
- 20A SPEC GRADE FOURPLEX CONVENIENCE OUTLET MOUNTED ABOVE COUNTER. VERIFY EXACT HEIGHT WITH ARCHITECTURAL ELEVATIONS.
- SPECIAL OUTLET AS NOTED ON DRAWINGS – VERIFY NEMA RATING BEFORE INSTALLATION
- SPECIAL OUTLET AS NOTED ON DRAWINGS

  X =
  C – MOUNTED IN CEILING RF – REFRIGERATOR
  DW – DISHWASHER GD – GARBAGE DISPOSAL PROVIDE SWITCH ABOVE COUNTER.
  MW – MICROWAVE UCR – UNDERCOUNTER REFRIGERATOR
  P – PEDISTAL MOUNTED VM – VENDING MACHINE
  PO – PEDIATRIC SAFE
- ISOLATED GROUNDING OUTLET AT +15" TO BOTTOM OR AS NOTED. "LEVITON" #5362-IG (ORANGE) RECEPTACLE WITH ISOLATED GROUND.
- 20A SPEC GRADE HALF SWITCHED DUPLEX RECEPTACLE AT +15" TO BOTTOM OR AS NOTED.
- DUAL COMPARTMENT POWER/TELE DATA POLE
- FLUSH FLOOR POWER OUTLET WITH FLUSH-IN-USE COVERS – WITH 20A SPEC GRADE RECEPTACLES DUPLEX OR FOURPLEX. HUBBELL, THOMAS & BETTS, CARLON OR EQUAL. RATED FOR SCRUB WATER.
- 20A SPEC GRADE GFCI DUPLEX RECEPTACLE AT +15" TO BOTTOM OR AS NOTED.
- 20A SPEC GRADE GFCI DUPLEX RECEPTACLE AT +6" ABOVE COUNTER TO BOTTOM OR AS NOTED.
- DROP CORD POWER OUTLET – WITH 20A SPEC GRADE RECEPTACLES DUPLEX OR FOURPLEX. HUBBELL, THOMAS & BETTS, CARLON OR EQUAL.
- "J" BOX FLUSH MOUNTED IN WALL FOR SYSTEMS FURNITURE POWER. COORDINATE EXACT LOCATION AND REQUIREMENTS WITH SUPPLIER PRIOR TO ROUGH-IN. ELECTRICAL CONTRACTOR IS RESPONSIBLE FOR FINAL CONNECTION TO SYSTEM FURNITURE.
- WIRE MOLD. LENGTH AND TYPE AS NOTED ON DRAWINGS. MOUNT AS NOTED ON THE DRAWINGS.

C. COMMUNICATIONS

- FLUSH FLOOR COMBINATION TELEPHONE/DATA OUTLET – PROVIDE 1" MIN CONDUIT TO ABOVE ACCESSIBLE CEILING. HUBBELL, THOMAS & BETTS, CARLON OR EQUAL. RATED FOR SCRUB WATER.
- DATA OUTLET AT +15" A.F.F. TO BOTTOM OF WALL FIXTURE OR AS NOTED. PROVIDE 3/4" CONDUIT STUBBED TO +4" ABOVE FINISHED CEILING.
- TELEPHONE OUTLET AT +15" A.F.F. TO BOTTOM OF WALL FIXTURES OR AS NOTED. PROVIDE 3/4" CONDUIT STUBBED TO +4" ABOVE FINISHED CEILING OR AS NOTED:

  X=
  P – PAY PHONE
  W – WALL PHONE OUTLET MOUNTED AT +44" A.F.F.
- COMBINATION TELEPHONE/DATA OUTLET AT +15" A.F.F. TO BOTTOM OF WALL FIXTURES OR AS NOTED. PROVIDE 3/4"C. STUBBED TO +4" ABOVE FINISHED CEILING.
- DIGITAL CABLE TELEVISION OUTLET
- TELEVISION OUTLET WITH DEVICES
- "J" BOX FLUSH MOUNTED IN WALL FOR SYSTEMS FURNITURE TELE/DATA WITH 1-1/4" EMPTY CONDUIT STUBBED ABOVE CEILING. COORDINATE EXACT LOCATION AND REQUIREMENTS WITH SUPPLIER PRIOR TO ROUGH-IN. ELECTRICAL CONTRACTOR IS RESPONSIBLE FOR FINAL CONNECTION TO SYSTEM FURNITURE.
- TELEPHONE TERMINAL BOARD "TMB", 3/4" PLYWOOD TELEPHONE MOUNTING BOARD WITH #6 COPPER GROUND & DEDICATED FOURPLEX CONVENIENCE OUTLET. FURNISH IN ACCORDANCE WITH TELEPHONE COMPANY'S REQUIREMENTS. SIZE AS NOTED ON DRAWINGS. PLYWOOD SHALL BE TYPE "CDX".

D. LIGHTING

- STANDARD SWITCH AND COVER PLATE WITH LOCKING DEVICE (BRADY NO. 2AF98 OR EQUAL)
- SINGLE POLE SWITCH MOUNTED AT +44" TO CENTER OF DEVICE OR AS NOTED.
- TWO POLE SWITCH MOUNTED AT +44" TO CENTER OF DEVICE OR AS NOTED.
- THREE WAY SWITCH MOUNTED AT +44" TO CENTER OF DEVICE OR AS NOTED.
- FOUR WAY SWITCH MOUNTED AT +44" TO CENTER OF DEVICE OR AS NOTED.
- SINGLE POLE SWITCH WITH PILOT LIGHT AT +44" TO CENTER OF DEVICE OR AS NOTED.
- 2000W SLIDE CONTROL DIMMER AT AT +44" TO CENTER OF DEVICE OR AS NOTED.
- SWITCH KEY OPERATED MTD AT +44" TO CENTER OF DEVICE OR AS NOTED.
- LOW VOLTAGE SLIDE CONTROL DIMMER WITH PRESET AT +44". CONTRACTOR SHALL SUPPLY SPECIFIC (ELECTRONIC AND/OR MAGNETIC) TO SUIT LOADS.
- WALL MOUNTED OCCUPANCY SENSOR. LUTRON–DUAL TECHNOLOGY OR EQUAL. IN RESTROOMS: LUTRON–ULTRASONIC. PROGRAM: MANUAL ON/AUTO OFF UNLESS NOTED OTHERWISE.
- SINGLE POLE UP–OFF–DOWN SWITCH FOR CONTROL OF PROJECTION SCREEN. MOUNTED AT +44" TO CENTER OF DEVICE OR AS NOTED.
- LOW VOLTAGE PUSH BUTTON CONTROL STATION AS NOTED. VERIFY MOUNTING HEIGHT.
- ROOF MOUNTED PHOTOCELL (AIM NORTH) INTERMATIC #EK4136S OR EQUAL.
- ASTRONOMIC ELECTRONIC 4 POLE LIGHTING TIMESWITCH, INTERMATIC #ET2845CR OR EQUAL.
- CEILING MOUNTED OCCUPANCY SENSOR 360°. LUTRON–DUAL TECHNOLOGY OR EQUAL. IN RESTROOMS: LUTRON–ULTRASONIC. IN WAREHOUSE: LUTRON–HIGHBAY. (WR) WIDE ANGLE (LR) LONG RANGE
- WALL/CEILING MOUNTED DUAL TECHNOLOGY OCCUPANCY SENSOR SHALL BE PROGRAMMED AS VACANCY SENSOR. MANUAL ON/AUTO OFF.
- OCCUPANCY SENSOR – POWER PACK OR SLAVE PACK.
- LED STRIP LIGHTING FIXTURE – AS NOTED ON DRAWINGS.
- LED LIGHTING FIXTURE – AS NOTED ON DRAWINGS SURFACE MOUNTED.
- RECESSED GRID W/FLEXIBLE CONNECTION.
- INDICATES NIGHTLIGHT (NL) AND/OR EMERGENCY FIXTURE WITH 1400 LUMEN MINIMUM (UNSWITCHED) – AS NOTED ON DRAWING.
- WALL MOUNTED LIGHTING FIXTURE – AS NOTED ON DRAWINGS.
- CEILING MOUNTED LIGHTING FIXTURE – AS NOTE ON DRAWINGS.
- LED HIGH/LOW BAY FIXTURE
- WALL WASH LIGHTING FIXTURE. AIM AS DIRECTED BY ARCHITECT.
- TRACK LIGHTING SYSTEM WITH TRACK FIXTURE HEADS AS INDICATED ON PLANS. VERIFY TYPE LINE OR LOW VOLTAGE.
- POLE MOUNTED AREA LIGHT (ARM MOUNTED) VERIFY HEIGHT SEE POLE DETAIL.
- POLE MOUNTED AREA LIGHT (POST TOP) VERIFY HEIGHT SEE POLE DETAIL.
- WALL PACK.
- SINGLE FACE EXIT SIGN, SEE LIGHTING FIXTURE SCHEDULE FOR SPECIFICATION. DIRECTIONAL ARROW AS INDICATED ON PLANS (CEILING OR WALL.)
- COMBINATION EMERGENCY EXIT SIGN WITH DUAL HEAD LIGHTS WITH EMERGENCY BATTERY BACK–UP.

D. LIGHTING CONTINUED

- DOUBLE FACE EXIT SIGN. SEE LIGHTING FIXTURE SCHEDULE FOR SPECIFICATION. DIRECTIONAL ARROW AS INDICATED ON PLANS (CEILING OR WALL)
- DUAL HEAD EMERGENCY BATTERY PACK, SEE LIGHTING FIXTURE SCHEDULE FOR SPECIFICATIONS.

E. MECHANICAL

- CONTACTOR – FURNISHED AND INSTALL BY OTHERS
- CONTACTOR – FURNISHED/INSTALLED BY ELECTRICAL CONTRACTOR SIZE AS NOTED
- MOTOR STARTER/CONTROLLER– FURNISHED WITH MOTOR.
- MOTOR STARTER/CONTROLLER – FURNISHED/INSTALLED BY ELECTRICAL CONTRACTOR.
- MOTOR – SIZE AS INDICATED ON DRAWINGS.
- DISCONNECT SWITCH – SIZE AND FUSES AS PER MANUFACTURER'S RECOMMENDATIONS (WEATHERPROOF WHERE OUTSIDE). N.F. INDICATES NON–FUSED.
- COMBINATION FUSIBLE DISCONNECT/MOTOR CONTROLLER – 30/3P WITH MIN. SIZE 1 MAGNETIC STARTER (UNLESS NOTED OTHERWISE). PROVIDE FUSES PER MANUFACTURER'S REQUIREMENTS. N.F. INDICATES NON–FUSED.
- HORSEPOWER RATED MANUAL MOTOR STARTER WITH THERMAL OVERLOAD(S). OVERLOAD HEATERS TO BE SIZED PER HORSEPOWER AND MANUFACTURER'S REQUIREMENTS.

F. FIRE ALARM

- FIRE ALARM PULL STATION AT +48".
- FIRE ALARM STROBE: +80" AFF OR 6" BELOW CEILING, WHICHEVER IS LOWER.
- FIRE ALARM HORN/STROBE: +80" AFF OR 6" BELOW CEILING, WHICHEVER IS LOWER.
- FIRE ALARM MAGNETIC DOOR HOLDER
- FIRE ALARM BELL
- FAAP — FIRE ALARM ANNUNCIATOR PANEL
- FACP — FIRE ALARM CONTROL PANEL
- FIRE ALARM HEAT DETECTOR.
- FIRE ALARM SMOKE DETECTOR.
- FIRE ALARM DUCT SMOKE DETECTOR.
- CARBON MONOXIDE DETECTOR.
- FIRE ALARM TAMPER SWITCH.
- FIRE ALARM FLOW SWITCH.
- SPEAKER.

G. ONE LINE DIAGRAM

- (M) METER, (S) SOCKET, (B) BLANK
- (M) METER, (S) SOCKET, (B) BLANK, WITH CURRENT TRANSFORMERS.
- BREAKER AS INDICATED.
- FUSED SWITCH.
- BREAKER WITH SHUNT TRIP (SIZE AS INDICATED)
- PULLOUT FUSE

H. SECURITY

- LOW VOLTAGE CARD READER WITH 3/4" EMPTY CONDUIT STUBBED ABOVE FINISHED CEILING SPACE
- LOW VOLTAGE KEYPAD
- SURVEILLANCE CAMERA

I. ABBREVIATIONS

A	AMPERE
AIC	AVAILABLE INTERRUPTING CURRENT
AI	ALUMINUM
AFC	AVAILABLE FAULT CURRENT
AFCI	ARC FAULT CIRCUIT INTERRUPTER
AFF	ABOVE FINISHED FLOOR
AFG	ABOVE FINISHED GRADE
AH	AIR HANDLER UNIT
APS	ARIZONA PUBLIC SERVICE – (UTILITY CO.)
C	CONDUIT
CCT	CORRECTED COLOR TEMP.
CRI	COLOR RENDERING INDEX
CU	COPPER
D	DEDICATED
DP	DUST – IGNITION PROOF
E	EXISTING
EC	EMPTY CONDUIT
EDF	ELECTRIC DRINKING FOUNTAIN
EF	EXHAUST FAN
EG	EQUIPMENT GROUND
EM	EMERGENCY LIGHT. BYPASS LOCAL SWITCHING AND PROVIDED BATTERY PACK.
GFCI	GROUND FAULT CIRCUIT INTERRUPTER
GFP	GROUND FAULT PROTECTION
GND	GROUND/BOND CONDUCTOR
GWH	GAS WATER HEATER
IAW	IN ACCORDANCE WITH
IG	ISOLATED GROUND
MCB	MAIN CIRCUIT BREAKER
MCC	MOTOR CONTROL CENTER
MLO	MAIN LUG ONLY
N	NEW ITEM
NR	NEW LOCATION OF RELOCATED EXISTING ITEM
NL	NIGHT LIGHT. BYPASS LOCAL SWITCHING.
PNL	PANELBOARD
R	EXISTING TO BE RELOCATED
SES	SERVICE ENTRANCE SECTION
SRP	SALT RIVER PROJECT – (UTILITY CO.)
SWBD	SWITCHBOARD
TEP	TUCSON ELECTRONIC POWER
TMB	3/4" PLYWOOD TELEPHONE MOUNTING BOARD WITH #6 CU. SOLID GROUND.
TTC	TELEPHONE TERMINAL CABINET (SIZE INDICATED ON DRAWINGS)
UFER	CONCRETE ENCASED ELECTRODE
UG	UNDERGROUND
UNO	UNLESS NOTED OTHERWISE
VA	VOLT AMPERES
W	WATT
WG	WIRE GUARD
WH	WATER HEATER
WP	WEATHERPROOF (RAIN TIGHT) WEATHER RESISTANT NEMA 3R OR NEMA 4 IN–USE
WR	WEATHER RESISTANT
X	EXISTING TO BE REMOVED
XP	EXPLOSION PROOF

ELECTRICAL SPECIFICATIONS

UPDATED: 08-07-2025

SOME SPECIFICATIONS MAY NOT BE USED FOR THIS PROJECT.

1.0 INTENT

1.1 FURNISH AND INSTALL A COMPLETE AND OPERATIONAL ELECTRICAL SYSTEM IN ACCORDANCE WITH PLANS AND SPECIFICATIONS.

1.2 ALL DRAWINGS ARE SCHEMATIC IN NATURE AND THE REQUIRED INSTALLATION IS NOT LIMITED TO WHAT IS SHOWN. ALL APPURTENANCES NECESSARY TO PROVIDE A COMPLETE AND OPERATIONAL SYSTEM ARE INCLUDED IN THE CONTRACTORS BID AND WORK.

2.0 GENERAL

2.1 THE CONTRACTOR SHALL VISIT THE JOB SITE AND FAMILIARIZE HIMSELF WITH ALL EXISTING CONDITIONS WHICH MAY AFFECT HIS BID OR WORK. NO ALLOWANCES WILL BE MADE FOR EXISTING CONDITIONS OR THE CONTRACTORS FAILURE TO ACCOMMODATE EXISTING CONDITIONS ON HIS BID.

2.2 IT IS THE CONTRACTORS RESPONSIBILITY TO OBTAIN CLARIFICATION OF ANY APPARENT CONFLICT OR INCONSISTENCY IN THE DRAWINGS, SPECIFICATION, OR DESIGN, PRIOR TO HIS BID AND IN WRITING WITH THE ENGINEER. OTHERWISE THE CONTRACTOR ACCEPTS RESPONSIBILITY TO CORRECT (AT HIS COST) ANY SUCH ITEMS TO MEET THE INTENT AS INTERPRETED BY THE ENGINEER.

2.3 ALL MATERIAL AND WORKMANSHIP SHALL CONFORM TO THE MOST RECENT ADOPTED EDITIONS OF THE NFPA, NATIONAL ELECTRIC CODE, IBC, APPLICABLE CITY AND STATE CODES AND ORDINANCES, THE AMERICANS WITH DISABILITIES ACT, E.P.A. REGULATIONS (INCLUDING EPACT 1992), INTERNATIONAL ENERGY CONSERVATION CODE (IECC)/TITLE 24/ASHRAE 90.1 AND UTILITY COMPANY REQUIREMENTS. THE FOREGOING CODES AND REGULATIONS ARE MINIMUM REQUIREMENTS AND ARE INCORPORATED IN THIS SPECIFICATION FOR THIS WORK BY REFERENCE.

2.4 THE CONTRACTOR SHALL COORDINATE AND PROVIDE INFORMATION AS REQUIRED TO ALL SERVING UTILITIES IN A TIMELY MANNER AS NECESSARY TO PROVIDE THE SERVICE REQUIRED AND MEET UTILITY REQUIREMENTS. IMMEDIATE COORDINATION WILL BE REQUIRED FOR MOST PROJECTS. FIELD COORDINATE ALL REQUIREMENTS WITH UTILITY Co. REPRESENTATIVES.

2.5 REFER TO ARCHITECTURAL, MECHANICAL, CIVIL, STRUCTURAL, AND/OR EQUIPMENT SUPPLIERS DRAWINGS AND SPECIFICATIONS FOR EXACT EQUIPMENT LOCATIONS, LOADS AND ADDITIONAL REQUIREMENTS. REPRESENTATIONS OF THE WORK SPECIFIC TO THE OTHER DISCIPLINES IS SHOWN ON THE ELECTRICAL DRAWINGS FOR CLARITY ONLY. THE CONTRACTOR ASSUMES RESPONSIBILITY FOR ALL EQUIPMENT OR SUPPLIES ALL EQUIPMENT SHALL BE INSTALLED STRICTLY PER MANUFACTURERS RECOMMENDATIONS. OTHERWISE THE CONTRACTOR ASSUMES RESPONSIBILITY (AT HIS COST) TO CORRECT AND REMEDY ANY INSTALLATION NOT IN COMPLIANCE WITH THE MANUFACTURES RECOMMENDATIONS AND INTENT AS INTERPRETED BY THE ENGINEER.

2.7 ANY VARIANCE OR EXCEPTIONS TO THE DRAWINGS AND SPECIFICATIONS MUST BE REQUESTED AND APPROVED IN WRITING. NO INTERIM APPROVALS WILL ONLY BE PROVIDED WHEN THE ENGINEER DETERMINES THIS TO BE JUSTIFIED AND MUST BE CONFIRMED IN WRITING TO BE VALID.

2.8 THE CONTRACTOR IS RESPONSIBLE TO OBTAIN ALL NECESSARY PERMITS, VARIANCES, AND APPROVALS, ETC. AND BE REQUIRED FOR COMPLETION OF THE WORK OF THIS WORK.

2.9 PRIOR TO ROUGH–IN, THE ELECTRICAL CONTRACTOR SHALL COORDINATE THE EXACT LOCATION OF ALL LIGHT FIXTURES AND WIRING DEVICES: TO INCLUDE MOUNTING HEIGHT AND LOCATION CONFLICTS WITH DUCTWORK, PIPING, ETC. SHALL BE REPORTED TO THE ENGINEER/ARCHITECT.

2.10 THE ELECTRICAL CONTRACTOR SHALL PROVIDE EQUIPMENT AND SUPPORT FOR PROGRESS AND FINAL INSPECTIONS. THIS INCLUDES COMPLETE ACCESS TO ALL EQUIPMENT. ADDITIONALLY A COMPLETE SET OF MARKUP PRINTS FOR 1000 VOLTS USED AND A 5% SUPPLY OF ALL LIGHT BULBS PROVIDED IN FIXTURES (TO A MAXIMUM OF 15 FOR EACH STYLE) SHALL BE PROVIDED TO THE OWNER AT FINAL INSPECTION.

2.11 RECONSTRUCTION (1) THE CONTRACTOR SHALL MAKE FUSES FOR 1000 VOLTS USED AND A 5% SUPPLY OF ALL LIGHT BULBS PROVIDED IN FIXTURES (TO A MAXIMUM OF EXISTING FACILITIES AND EQUIPMENT SHALL REQUIRE COMPLETE RENOVATION (MAKE GOOD AS NEW) FOR ALL EQUIPMENT UPON WHICH WORK IS PERFORMED OR EQUIPMENT WHICH IS AFFECTED BY THE WORK PERFORMED. THIS WILL INCLUDE THESE FOLLOWING SPECIFICATIONS:

2.11.1 VERIFICATION OF EXISTING SES COMPLIANCE WITH NEC "GROUNDING" ARTICLES.

2.12.2 VERIFICATION OF CABLE SIZE AND AMPACITY OF EXISTING FEEDERS AND BRANCH CIRCUITS PER NEC TABLES.

2.11.3 EXISTING LIGHT FIXTURES TO BE REUSED MUST BE CLEANED, RE–LAMPED, AND RESTORED TO LIKE NEW CONDITION.

2.11.4 EXISTING PANEL BOARDS, SWITCH BOARDS, AND TRANSFORMERS WHICH ARE INCLUDED IN THE PROJECT WORK SHALL HAVE PREVENTATIVE MAINTENANCE PERFORMED TO INCLUDE RE–TORQUING OF ALL LUGS, CLEANING AND INSPECTION.

2.11.5 VERIFY PROPER WORKING CONDITION OF ALL EXISTING EMERGENCY FIXTURES AND EXIT SIGNS AS REQUIRED REPAIR OR REPLACE AS REQUIRED.

IN THE EVENT THAT INSPECTION REVEALS DISCREPANCIES AND/OR NONCOMPLIANCE THE OWNER AND THE ENGINEER SHALL BE NOTIFIED IN WRITING, AND EQUIPMENT BROUGHT INTO COMPLIANCE.

3.0 MATERIALS AND METHODS

3.1 THE USE OF **EMT** IS ACCEPTABLE IN ACCORDANCE WITH NEC ARTICLE "ELECTRICAL METALLIC TUBING". EMT SHALL NOT BE USED WHERE IT IS SUBJECT TO SEVERE PHYSICAL DAMAGE. EMT SHALL NOT BE COMPRESSION TYPE. MINIMUM TRADE CONDUIT SIZE IS 1/2" AND 3/4" FOR HOME RUNS.

3.2 **CONDUCTORS** SHALL BE COPPER (UNLESS NOTED OTHERWISTY). MINIMUM LINE VOLTAGE WIRE SIZE IS #12 A.W.G. #6 AND SMALLER SHALL HAVE THHN/THWH INSULATION. #4 AND LARGER SHALL HAVE XHHW INSULATION. ALL CONDUCTORS SHALL HAVE 90° RATED INSULATION. ALL 120V, 20A BRANCH CIRCUIT CONDUCTORS (#12) OVER 100' IN LENGTH TO BE #10 AWG MINIMUM. ALL 277V, 20A BRANCH CIRCUIT CONDUCTORS (#12) OVER 200' IN LENGTH TO BE #10T5 MINIMUM.

3.3 WHEN SEPARATE BRANCH CIRCUIT NEUTRAL CONDUCTORS ARE USED WITH EACH PHASE CONDUCTOR OR SYSTEMS FURNITURE INDICATES, THE MINIMUM NEUTRAL CONDUCTOR SIZE SHALL BE #10 A.W.G. STRANDED COPPER.

3.4 ALL WIRING DEVICES SHALL BE OF A CONSISTENT HEIGHT AND INCLUDE PROTECTION OF OPERATIONAL DEVICES AND METERS FROM PHYSICAL DAMAGE.

3.5 PROVIDE CONCRETE HOUSEKEEPING PADS FOR FREESTANDING ELECTRICAL SERVICE ENTRANCE EQUIPMENT PER LOCAL UTILITY COMPANY SPECIFICATIONS.

3.6 **SERVICE COORDINATION STUDY**

3.10.1 **DESCRIPTION**

3.10.1.1 WHEN ADJUSTABLE TRIP CIRCUIT BREAKERS OR 2–TIER GROUND FAULT SYSTEM IS SPECIFIED, PROVIDE A SHORT–CIRCUIT AND PROTECTIVE DEVICE COORDINATION STUDY FOR THE ELECTRICAL DISTRIBUTION SYSTEM. THE INTENT OF THESE STUDIES ARE TO VERIFY THAT THE SPECIFIED AND SUPPLIED EQUIPMENT ARE PROPERLY RATED, CORRECTLY APPLIED, AND WITHIN INDUSTRY AND MANUFACTURER'S TOLERANCES.

3.10.1.2 THE SHORT CIRCUIT STUDY SHALL INCLUDE ALL PORTIONS OF THE ELECTRICAL DISTRIBUTION SYSTEM FROM THE NORMAL AND ALTERNATE SOURCES OF POWER THROUGH THE DISTRIBUTION SYSTEM DOWN TO THE SMALLEST PROTECTIVE DEVICE. THE SHORT CIRCUIT STUDY SHALL CONSIDER OPERATIONS DURING NORMAL CONDITIONS, ALTERNATE OPERATIONS, EMERGENCY POWER CONDITIONS AND ANY OTHER OPERATIONS WHICH COULD RESULT IN MAXIMUM FAULT CONDITIONS.

6.10.1.3 THE COORDINATION STUDY SHALL DETERMINE THE CORRECT SETTINGS FOR THE PROTECTIVE DEVICES WHICH WILL MINIMIZE THE DAMAGE CAUSED BY AN ELECTRICAL FAULT AND ALLOW FOR SELECTIVE COORDINATION BETWEEN THE DEVICES. THE COORDINATION STUDY SHALL INCLUDE THE CLOSEST UPSTREAM UTILITY PROTECTIVE DEVICE DOWN TO THE PANELBOARD MAIN, BRANCH OR FEEDER CIRCUIT BREAKERS. THE COORDINATION STUDY SHALL CONSIDER OPERATION DURING NORMAL CONDITIONS, ALTERNATE OPERATIONS AND DURING EMERGENCY POWER CONDITIONS.

6.10.2 **QUALIFICATIONS**

6.10.2.1 THE CONTRACTOR SHALL HAVE THE COORDINATION STUDY PREPARED BY QUALIFIED ENGINEERS OF AN INDEPENDENT CONSULTANT AND OR MANUFACTURER. THE CONSULTANT/MANUFACTURER SHALL BE AN EXPERIENCED REGISTERED PROFESSIONAL ELECTRICAL ENGINEER (LICENSED IN THE STATE WHERE THE PROJECT IS COMPLETED) SPECIALIZING IN PERFORMING POWER SYSTEM STUDIES.

6.10.3 **SUBMITTALS**

6.10.3.1 THE CONTRACTOR SHALL SUBMIT THE POWER SYSTEM STUDIES IN CONJUNCTION WITH THE EQUIPMENT SUBMITTALS. THE ELECTRICAL SUBMITTALS WILL BE REVIEWED BUT WILL NOT BE APPROVED UNLESS THE POWER SYSTEM STUDIES HAVE BEEN RECEIVED AND REVIEWED.

6.11 **PROTECTIVE DEVICE EVALUATION STUDY**

6.11.1 ALL BOARDMENTS OF THE CURRENT NATIONAL ELECTRICAL CODE AND NFPA 5000 SHALL BE ADHERED TO.

6.11.2 THE COORDINATION STUDY SHALL INCLUDE THE CLOSEST UPSTREAM UTILITY PROTECTIVE DEVICE DOWN TO THE PANELBOARD MAIN, BRANCH, OR FEEDER CIRCUIT BREAKERS. PREPARE THE COORDINATION CURVES TO DETERMINE THE REQUIRED SETTINGS OF PROTECTIVE DEVICES TO ASSURE SELECTIVE COORDINATION.

6.11.3 THE PHASE AND GROUND OVERCURRENT PROTECTION SHALL BE INCLUDED, AS WELL AS SETTINGS FOR ALL OTHER ADJUSTABLE PROTECTIVE DEVICES.

6.11.4 GRAPHICALLY ILLUSTRATE ON LOG–LOG PAPER THAT ADEQUATE TIME SEPARATION EXISTS BETWEEN DEVICES. SUFFICIENT CURVES SHALL BE USED TO CLEARLY INDICATE THE COORDINATION ACHIEVED BETWEEN DEVICES. REASONABLE COORDINATION INTERVALS AND SEPARATION OF CHARACTERISTIC CURVES SHALL BE MAINTAINED. PLOT THE SPECIFIC TIME–CURRENT CHARACTERISTICS OF EACH PROTECTIVE DEVICE IN SUCH A MANNER THAT THE UPSTREAM DEVICES WILL BE CLEARLY DEPICTED ON THE SHEET.

6.11.5 THE FOLLOWING SPECIFIC INFORMATION SHALL ALSO BE SHOWN ON THE COORDINATION CURVES:

6.11.5.1 DEVICE IDENTIFICATIONS.

6.11.5.2 TIME AND CURRENT RATIO FOR CURVES.

6.11.5.3 FUSE, CIRCUIT BREAKER, AND RELAY CURVES, SHOWING COMPLETE OPERATING BANDS OF LOW VOLTAGE CIRCUIT BREAKER TRIP CURVES.

6.11.5.4 LOW VOLTAGE EQUIPMENT CIRCUIT BREAKER TRIP DEVICES, INCLUDING MANUFACTURERS TOLERANCE BANDS.

6.11.5.5 PERTINENT TRANSFORMER FULL–LOAD CURRENTS AT 100 AND 600 PERCENT.

6.11.5.6 GROUND FAULT PROTECTIVE DEVICE SETTINGS.

6.11.5.7 OTHER SYSTEM LOAD CURRENTS SHOWN FOR LARGEST BRANCH CIRCUIT AND FEEDER CIRCUIT BREAKER IN EACH MOTOR CONTROL CENTER AND PANELBOARD.

6.11.6 DEVELOP A TABLE TO SUMMARIZE THE SETTINGS SELECTED FOR THE PROTECTIVE DEVICES. INCLUDE IN THE TABLE THE FOLLOWING:

6.11.6.1 DEVICE IDENTIFICATIONS.

6.11.6.2 CURRENT TRANSFORMER RATIO, RELAY TAP, TIME DELAY AND INSTANTANEOUS PICKUP.

6.11.6.3 CIRCUIT BREAKER SENSOR RATING, LONG–TIME, SHORT–TIME AND INSTANTANEOUS SETTINGS AND TIME BANDS.

6.11.6.4 FUSE RATING AND TYPE.

6.11.6.5 GROUND FAULT PICKUP AND TIME DELAY.

6.12 **ANALYSIS**

6.12.1 ANALYZE THE SHORT CIRCUIT CALCULATIONS AND HIGHLIGHT ANY EQUIPMENT THAT IS DETERMINED TO BE UNDERRATED AS SPECIFIED OR NOT COORDINATED. PROPOSE APPROACHES TO EFFECTIVELY PROTECT THE UNDERRATED EQUIPMENT. PROPOSED MAJOR CORRECTIVE MODIFICATIONS WILL BE TAKEN UNDER ADVISEMENT BY THE ENGINEER AND THE CONTRACTOR WILL BE GIVEN FURTHER INSTRUCTIONS.

6.12.2 AFTER DEVELOPING THE COORDINATION CURVES, HIGHLIGHT AREAS LACKING COORDINATION. FOR EACH SHEET, PRESENT A TECHNICAL EVALUATION WITH A DISCUSSION OF THE LOGICAL COMPROMISES FOR BEST COORDINATION.

6.13 **REPORT**

THE RESULTS OF THE POWER SYSTEM STUDY SHALL BE SUMMARIZED IN A FINAL REPORT. THE REPORT SHALL INCLUDE THE FOLLOWING SECTIONS:

6.13.1 PROTECTIVE DEVICE TIME VERSUS CURRENT COORDINATION CURVES, TABULATIONS OF RELAY AND CIRCUIT BREAKER TRIP SETTINGS, FUSE SELECTION AND COMMENTARY PLOTTED SAME.

6.13.2 COPIES OF THE MANUFACTURERS TIME CURRENT CURVES FOR THE DEVICES STUDIED AND PLOTTED ON THE TIME CURRENT CURVES.

7.0 DISTRIBUTION

7.1 **PANELBOARDS** (EXISTING): ADD CIRCUIT BREAKERS (FULL SIZED BREAKERS) AS REQUIRED FOR CIRCUITING. MATCH PRECISELY BRAND AND PROVIDE A.I.C. RATING AS INDICATED ON DRAWINGS. TANDEM AND PONY BREAKERS ARE NOT PERMITTED. ALL LUGS OR CONNECTORS TO BE 60°C FOR PANEL LESS THAN OR EQUAL 100 AMPS AND 75°C RATED OF GREATER THAN 100AMPS MINIMUM. PANELBOARD CABINET SHALL BE EQUIPPED WITH PIANO HINGES WITH DOOR IN DOOR CONSTRUCTION.

7.2 **PANELBOARDS** (NEW): SHALL BE RATED AS SHOWN ON DRAWINGS WITH PLATED COPPER BUSSING. PROVIDE NEMA ENCLOSURES AS REQUIRED BY CODE FOR REGULATION. BACK BOXES ENLARGED FOR DOUBLE NEUTRALS AND LUGS CAPABLE OF OVERSIZED ISOLATED GROUND AND NORMAL GROUND BUS. ALL LUGS OR CONNECTORS TO BE 60°C FOR PANEL LESS THAN OR EQUAL 100 AMPS AND 75°C RATED OF GREATER THAN 100AMPS MINIMUM. PANELBOARD CABINET SHALL BE EQUIPPED WITH PIANO HINGES WITH DOOR IN DOOR CONSTRUCTION.

7.3 **CIRCUIT BREAKERS** WILL BE SWITCH RATED AND AMBIENT COMPENSATED FOR ALL CIRCUITS. PROVIDE SWITCHED NEUTRALS ON ALL CIRCUIT BREAKERS FEEDING CLASS 1 AND CLASS 2 AREAS WITH NEUTRALS. GFCI ON CIRCUITS WITH NEUTRALS TO DEVICES ABOVE CLASSIFIED AREAS. ALL LIGHTING PANELS/CIRCUIT BREAKERS SHALL BE RATED FOR CONTINUOUS DUTY. HACR RATED BREAKERS SHALL BE INSTALLED FOR ALL HVAC CIRCUITS CONTAINING MULTIPLE MOTOR LOADS.

7.4 ALL EQUIPMENT (PANELS, DISCONNECT SWITCHES, STARTERS, ETC.) WILL BE MARKED WITH BLACK PHENOLIC ENGRAVERS STOCK TAGS WITH 1/4" HIGH LETTERS DESCRIBING EACH ITEM. CONDUCTORS WILL BE MARKED AT ALL TERMINATION AND JUNCTION POINTS (PANELS, JUNCTION BOXES, ETC.) WITH LABELS BEARING THE PANEL AND CIRCUIT NUMBER WHICH FEEDS EACH CONDUCTOR (PER NEC 210.5). ALL **PANELBOARDS** ALL HAVE TYPED DIRECTORY IDENTIFYING ALL CIRCUITS AND SPACES.

7.5 ACCEPTABLE MANUFACTURERS FOR **PANELBOARDS, SWITCHBOARDS, AND TRANSFORMERS** SHALL BE PER SECTION 3.15 OF THIS SPECIFICATION. TRANSFORMERS 15 KVA AND ABOVE SHALL BE 150°C TEMPERATURE RISE ABOVE AMBIENT. ALL INSULATING MATERIALS TO BE IN ACCORDANCE WITH NEMA STD–1972 STANDARDS FOR A 220°C UL COMPONENT RECOGNIZED INSULATION SYSTEM. SINGLE PHASE TRANSFORMERS 15 KVA THROUGH 50 KVA, AND THREE PHAS